# MINIMAX ROBUST TIME-FREQUENCY FILTERS FOR NONSTATIONARY SIGNAL ESTIMATION\*

Gerald Matz and Franz Hlawatsch

Institute of Communications and Radio-Frequency Engineering, Vienna University of Technology

Gusshausstrasse 25/389, A-1040 Wien, Austria

phone: +43 1 58801 3515, fax: +43 1 5870583, email: gmatz@aurora.nt.tuwien.ac.at

web: http://www.nt.tuwien.ac.at/dspgroup/time.html

## ABSTRACT

We introduce minimax robust time-varying Wiener filters and show a result that facilitates their calculation. Reformulation in the time-frequency domain yields simple closedform expressions of *minimax robust time-frequency Wiener filters* based on three different uncertainty models. For one of these filters, an efficient implementation using the multiwindow Gabor transform is proposed.

#### **1** INTRODUCTION

We consider the estimation of a nonstationary random signal s(t) from an observation r(t) = s(t) + n(t), where n(t)is nonstationary noise uncorrelated with s(t), by means of a linear, time-varying system **H**. The resulting mean square error (MSE)  $e(\mathbf{H}; \mathbf{R}_s, \mathbf{R}_n) \triangleq \mathbb{E}\{\|\mathbf{H}r - s\|_2^2\}$  is given by<sup>1</sup>

$$e(\mathbf{H};\mathbf{R}_s,\mathbf{R}_n) = \operatorname{tr}\left\{ (\mathbf{I}-\mathbf{H})\mathbf{R}_s(\mathbf{I}-\mathbf{H})^+ + \mathbf{H}\mathbf{R}_n\mathbf{H}^+ \right\}.$$
(1)

The MSE is minimized by the time-varying Wiener filter [1]

$$\mathbf{H}_{W} \triangleq \arg\min_{\mathbf{H}} e(\mathbf{H}; \mathbf{R}_{s}, \mathbf{R}_{n}) = \mathbf{R}_{s}(\mathbf{R}_{s} + \mathbf{R}_{n})^{-1}, \quad (2)$$

and the minimal MSE can be expressed as

$$e_{\min}(\mathbf{R}_s, \mathbf{R}_n) \triangleq e(\mathbf{H}_W; \mathbf{R}_s, \mathbf{R}_n) = \operatorname{tr} \{ \mathbf{R}_s (\mathbf{R}_s + \mathbf{R}_n)^{-1} \mathbf{R}_n \}.$$
(3)

The Wiener filter's sensitivity to deviations of the actual correlations from the nominal correlations motivates the use of *minimax robust Wiener filters*. This paper extends the robust Wiener filters proposed in [2]–[5] for *stationary* processes to the nonstationary case (see also [6, 7]). Complementing the introduction of robust time-varying Wiener filters in [8], Section 2 provides a fundamental result that facilitates the calculation of such filters. A further simplification is achieved in Section 3 by a time-frequency formulation. Explicit expressions of "minimax robust time-frequency Wiener filters" are derived for three uncertainty models. Finally, simulation results are presented in Section 4.

#### 2 ROBUST TIME-VARYING WIENER FILTER

By definition, the minimax robust time-varying Wiener filter  $\mathbf{H}_R$  optimizes the worst-case performance within uncertainty classes S,  $\mathcal{N}$  for the correlations  $\mathbf{R}_s$ ,  $\mathbf{R}_n$ :

$$\mathbf{H}_{R} \triangleq \arg\min_{\mathbf{H}} \max_{\substack{\mathbf{R}_{s} \in S \\ \mathbf{R}_{n} \in \mathcal{N}}} e(\mathbf{H}; \mathbf{R}_{s}, \mathbf{R}_{n}).$$
(4)

\*Funding by FWF grant P11904-TEC.

The uncertainty classes S,  $\mathcal{N}$  model our uncertainty about the actual correlations. All  $\mathbf{R}_s \in S$  are assumed to have the same trace (mean energy of s(t))  $\bar{E}_s \triangleq \mathrm{E}\{\|s\|_2^2\} = \mathrm{tr}\{\mathbf{R}_s\}$ , and similarly for  $\mathbf{R}_n \in \mathcal{N}$ .

The calculation of  $\mathbf{H}_R$  simplifies if

$$\min_{\mathbf{H}} \max_{\substack{\mathbf{R}_s \in S \\ \mathbf{R}_n \in \mathcal{N}}} e(\mathbf{H}; \mathbf{R}_s, \mathbf{R}_n) = \max_{\substack{\mathbf{R}_s \in S \\ \mathbf{R}_n \in \mathcal{N}}} \min_{\substack{\mathbf{H}}} e(\mathbf{H}; \mathbf{R}_s, \mathbf{R}_n), \quad (5)$$

since  $\min_{\mathbf{H}} e(\mathbf{H}; \mathbf{R}_s, \mathbf{R}_n)$  is achieved by the ordinary Wiener filter  $\mathbf{H}_W = \mathbf{R}_s(\mathbf{R}_s + \mathbf{R}_n)^{-1}$  in (2). Hence, when (5) is valid,  $\mathbf{H}_R$  is equal to the *ordinary* Wiener filter

$$\mathbf{H}_{R} = \mathbf{H}_{W}^{L} \triangleq \mathbf{R}_{s}^{L} \left(\mathbf{R}_{s}^{L} + \mathbf{R}_{n}^{L}\right)^{-1}$$

obtained for those correlations  $\mathbf{R}_{s}^{L}$ ,  $\mathbf{R}_{n}^{L}$  that are *least fa*vorable in the sense that they maximize  $e_{\min}(\mathbf{R}_{s}, \mathbf{R}_{n}) = \min_{\mathbf{H}} e(\mathbf{H}; \mathbf{R}_{s}, \mathbf{R}_{n})$  among all  $\mathbf{R}_{s} \in \mathcal{S}$  and  $\mathbf{R}_{n} \in \mathcal{N}$ , i.e.,

$$\mathbf{R}_{s}^{L}, \mathbf{R}_{n}^{L}) = \arg \max_{\substack{\mathbf{R}_{s} \in S \\ \mathbf{R}_{n} \in \mathcal{N}}} e_{\min}(\mathbf{R}_{s}, \mathbf{R}_{n}), \qquad (6)$$

with  $e_{\min}(\mathbf{R}_s, \mathbf{R}_n)$  given by (3).

It can be shown [9] that the pivotal relation (5) holds if and only if there exists a *saddle point* of  $e(\mathbf{H}; \mathbf{R}_s, \mathbf{R}_n)$ , i.e., a filter  $\mathbf{H}_L$  and correlations  $\mathbf{R}_s^L$ ,  $\mathbf{R}_n^L$  satisfying

$$e(\mathbf{H}_L; \mathbf{R}_s, \mathbf{R}_n) \leq e(\mathbf{H}_L; \mathbf{R}_s^L, \mathbf{R}_n^L) \leq e(\mathbf{H}; \mathbf{R}_s^L, \mathbf{R}_n^L)$$
 (7)

for all **H** and  $\mathbf{R}_s \in S$ ,  $\mathbf{R}_n \in \mathcal{N}$ . The right-hand inequality in (7) is trivially satisfied by choosing  $\mathbf{H}_L = \mathbf{H}_W^L$  since  $\mathbf{H}_W^L$ minimizes  $e(\mathbf{H}; \mathbf{R}_s^L, \mathbf{R}_n^L)$ . A necessary and suffient condition for the left-hand inequality in (7) is provided by the following theorem whose proof is outlined in the Appendix.

**Theorem 2.1.** For convex<sup>2</sup> uncertainty classes  $\mathcal{S}$ ,  $\mathcal{N}$ , there is  $e(\mathbf{H}_{W}^{L}; \mathbf{R}_{s}, \mathbf{R}_{n}) \leq e(\mathbf{H}_{W}^{L}; \mathbf{R}_{s}^{L}, \mathbf{R}_{n}^{L})$  with  $\mathbf{H}_{W}^{L} = \mathbf{R}_{s}^{L} (\mathbf{R}_{s}^{L} + \mathbf{R}_{n}^{L})^{-1}$  if and only if  $\mathbf{R}_{s}^{L}$  and  $\mathbf{R}_{n}^{L}$  are least favorable correlations as defined in (6).

Hence, we have finally simplified the calculation of  $\mathbf{H}_R$  to the convex optimization problem (6).

### 3 ROBUST TIME-FREQUENCY WIENER FILTER

A further simplification will be achieved by a time-frequency (TF) reformulation in terms of the Weyl symbol  $L_{\mathbf{H}}(t, f)$  of a linear time-varying system  $\mathbf{H}$  [10]–[12] and the Wigner-Ville spectrum (WVS)  $\overline{W_x}(t, f)$  of a nonstationary random process x(t) [13]–[15]. This will allow us to replace the calculus of operators by the simpler calculus of functions. We

<sup>&</sup>lt;sup>1</sup>Here,  $\mathbf{R}_s$  and  $\mathbf{R}_n$  denote the correlation operators of s(t) and n(t), respectively. The correlation operator  $\mathbf{R}_x$  of a (generally nonstationary) random process x(t) is the positive (semi-)definite linear operator whose kernel equals  $r_x(t, t') = \mathbb{E} \{x(t) \ x^*(t')\}$ . In a discrete-time setting,  $\mathbf{R}_x$  would be a matrix.

<sup>&</sup>lt;sup>2</sup>A set S is convex if from  $\mathbf{R}_1 \in S$  and  $\mathbf{R}_2 \in S$  it follows that  $\alpha \mathbf{R}_1 + (1-\alpha)\mathbf{R}_2 \in S$  for  $0 \le \alpha \le 1$ .

require the processes s(t) and n(t) to be jointly underspread [15], i.e., to feature only a limited amount of TF correlation. For underspread processes, the following approximate TF formulations<sup>3</sup> of  $e(\mathbf{H}; \mathbf{R}_s, \mathbf{R}_n)$  in (1),  $\mathbf{H}_W$  in (2), and  $e_{\min}(\mathbf{R}_s, \mathbf{R}_n)$  in (3) can be derived [16],

$$e(\mathbf{H}; \mathbf{R}_{s}, \mathbf{R}_{n}) \approx \tilde{e}(L_{\mathbf{H}}; \overline{W_{s}}, \overline{W_{n}}) \triangleq \int_{t} \int_{f} \left[ \left| 1 - L_{\mathbf{H}}(t, f) \right|^{2} \cdot \overline{W_{s}}(t, f) + \left| L_{\mathbf{H}}(t, f) \right|^{2} \overline{W_{n}}(t, f) \right] dt df ,$$

$$L_{\mathbf{H}_{W}}(t, f) \approx L_{\widetilde{\mathbf{H}}_{W}}(t, f) \triangleq \frac{\overline{W_{s}}(t, f)}{\overline{W_{s}}(t, f) + \overline{W_{n}}(t, f)} , \quad (8)$$

$$e_{\min}(\mathbf{R}_{s}, \mathbf{R}_{n}) \approx \tilde{e}_{\min}(W_{s}, W_{n})$$

$$\triangleq \int_{t} \int_{f} \frac{\overline{W_{s}}(t, f) \overline{W_{n}}(t, f)}{\overline{W_{s}}(t, f) + \overline{W_{n}}(t, f)} dt df .$$
(9)

In analogy to (4), we define the minimax robust TF Wiener filter  $\widetilde{\mathbf{H}}_R$  via its Weyl symbol as

$$L_{\widetilde{\mathbf{H}}_{R}}(t,f) \triangleq \arg\min_{\substack{L_{\mathbf{H}} \\ \overline{W_{s}} \in \widetilde{S} \\ \overline{W_{n}} \in \widetilde{\mathcal{N}}}} \max_{\widetilde{W_{s}} \in \widetilde{\mathcal{N}}} \widetilde{e}(L_{\mathbf{H}}; \overline{W_{s}}, \overline{W_{n}})$$

where  $\widetilde{S}$  and  $\widetilde{\mathcal{N}}$  are uncertainty classes<sup>4</sup> for  $\overline{W_s}(t, f)$  and  $\overline{W_n}(t, f)$ . Assuming  $\widetilde{S}$  and  $\widetilde{\mathcal{N}}$  to be convex and proceeding in analogy to Section 2 and the stationary case, we can show that  $\widetilde{\mathbf{H}}_R$  equals the ordinary TF Wiener filter in (8),

$$L_{\widetilde{\mathbf{H}}_{R}}(t,f) = L_{\widetilde{\mathbf{H}}_{W}^{L}}(t,f) = \frac{\overline{W}_{s}^{L}(t,f)}{\overline{W}_{s}^{L}(t,f) + \overline{W}_{n}^{L}(t,f)}, \quad (10)$$

calculated for least favorable pseudo-WVS

$$\left(\overline{W_s}^L, \overline{W_n}^L\right) \ = \ rg\max_{\substack{\overline{W_s} \in \widetilde{\mathcal{S}} \\ \overline{W_n} \in \widetilde{\mathcal{N}}}} \widetilde{e}_{\min}(\overline{W_s}, \overline{W_n})$$

with  $\tilde{e}_{\min}(\overline{W_s}, \overline{W_n})$  given by (9). This generalizes a similar result in the stationary case [4]. From  $L_{\widetilde{\mathbf{H}}_R}(t, f)$ ,  $\widetilde{\mathbf{H}}_R$  can be obtained by an inverse Weyl transform [10, 11].

Next, we propose three different definitions of TF uncertainty classes  $\tilde{\mathcal{S}}, \tilde{\mathcal{N}}$  and we provide closed-form expressions for the respective robust TF Wiener filters  $\tilde{\mathbf{H}}_{R}$ .

*p*-**Point Model.** Let  $\{\mathcal{R}_i\}_{i=1,2,...,N}$  be a partition of the TF plane, i.e.,  $\bigcup_{i=1}^{N} \mathcal{R}_i = \mathbb{R}^2$  and  $\mathcal{R}_i \cap \mathcal{R}_j = \emptyset$  for  $i \neq j$ . Extending the stationary case definition in [3, 5], so-called *p*-point uncertainty classes can be defined for WVS as [8]

$$\widetilde{\mathcal{S}} = \left\{ \overline{W_s}(t,f) : \iint_{\mathcal{R}_i} \overline{W_s}(t,f) \, dt \, df = s_i \,, \quad i = 1, 2, \dots, N \right\}$$
$$\widetilde{\mathcal{N}} = \left\{ \overline{W_n}(t,f) : \iint_{\mathcal{R}_i} \overline{W_n}(t,f) \, dt \, df = n_i \,, \quad i = 1, 2, \dots, N \right\},$$

i.e., as the sets that contain all pseudo-WVS having prescribed energies  $s_i \ge 0$  and  $n_i \ge 0$  in prescribed TF regions  $\mathcal{R}_i$ . The sets  $\widetilde{\mathcal{S}}, \widetilde{\mathcal{N}}$  are easily shown to be convex.

A TF reformulation of the results in [8, 3] yields as least favorable pseudo-WVS  $\overline{W}_s^L(t, f) = \sum_{i=1}^N \overline{W}_{s,i}(t, f)$  and

 $\overline{W}_{n}^{L}(t,f) = \sum_{i=1}^{N} \overline{W}_{n,i}(t,f)$ , where  $\overline{W}_{s,i}(t,f)$  and  $\overline{W}_{n,i}(t,f)$  are arbitrary nonnegative functions that are zero outside  $\mathcal{R}_{i}$  and satisfy  $n_{i}\overline{W}_{s,i}(t,f) = s_{i}\overline{W}_{n,i}(t,f)$ . The robust TF Wiener filter in (10) is then obtained as

$$L_{\widetilde{\mathbf{H}}_{R}}(t,f) = \sum_{i=1}^{N} w_i I_{\mathcal{R}_i}(t,f) \quad \text{with} \ w_i = \frac{s_i}{s_i + n_i}, \quad (11)$$

where  $I_{\mathcal{R}_i}(t, f)$  is the indicator function of  $\mathcal{R}_i$ . Note that  $L_{\widetilde{\mathbf{H}}_R}(t, f)$  is piecewise constant, expressing constant TF weighting in a given TF region  $\mathcal{R}_i$ . Furthermore,  $\widetilde{\mathbf{H}}_R$  can be shown to yield a constant TF MSE  $\tilde{e}(L_{\widetilde{\mathbf{H}}_R}; \overline{W_s}, \overline{W_n}) = \sum_{i=1}^{N} \frac{s_i n_i}{s_i + n_i}$  for all  $\overline{W_s} \in \widetilde{S}$ ,  $\overline{W_n} \in \widetilde{\mathcal{N}}$ .

It has been shown [8] that  $\widetilde{\mathbf{H}}_R$  in (11) is a good approximation to the analogous robust time-varying Wiener filter  $\mathbf{H}_R$  defined according to (4). Thus, our TF formulation of robust time-varying Wiener filters is valid, and (since  $\mathbf{H}_R$ is not based on an underspread assumption)  $\widetilde{\mathbf{H}}_R$  is robust also for processes that are not underspread.

An intuitive and computationally efficient approximate TF implementation of the robust TF filter  $\tilde{\mathbf{H}}_{R}$  in (11) exists if the partition  $\{\mathcal{R}_{i}\}$  corresponds to a uniform rectangular tiling of the TF plane, i.e., the TF regions are chosen as  $\mathcal{R}_{k,l} = [kT - T/2, kT + T/2) \times [lF - F/2, lF + F/2)$  with  $TF = M \in \mathbb{N}$  (note that now we use a double index). Let  $\{x^{(m)}(t)\}_{m=1,2,\dots,M}$  denote an orthonormal basis for the signal subspace  $\mathcal{X}_{0,0}$  corresponding to the TF rectangle  $\mathcal{R}_{0,0}$  (this correspondence is defined in [17]). Since  $\mathcal{R}_{k,l}$  is obtained from  $\mathcal{R}_{0,0}$  through a TF shift by (kT, lF), an orthonormal basis for the signal subspace  $\mathcal{X}_{k,l}$  corresponding to  $\mathcal{R}_{k,l}$  is given by  $\{x_{k,l}^{(m)}(t) = x^{(m)}(t-kT) e^{j2\pi lFt}\}_{m=1,2,\dots,M}$  [17]. We now propose to approximate  $\tilde{\mathbf{H}}_{R}$  in (11) (to be more precise,  $\mathbf{H}_{R}$ ) by the filter  $\hat{\mathbf{H}}_{R} \triangleq \sum_{k=-\infty}^{\infty} \sum_{l=-\infty}^{\infty} w_{k,l} \mathbf{P}_{k,l}$  with  $w_{k,l} = \frac{s_{k,l}}{s_{k,l}+\pi_{k,l}}$ , where  $\mathbf{P}_{k,l}$  is the orthogonal projection operator on  $\mathcal{X}_{k,l}$ .

$$(\widehat{\mathbf{H}}_R r)(t) = \sum_{m=1}^M \sum_{k=-\infty}^\infty \sum_{l=-\infty}^\infty w_{k,l} G_r^{(m)}(k,l) x_{k,l}^{(m)}(t),$$

with the Gabor coefficients [18]  $G_r^{(m)}(k,l) = \langle r, x_{k,l}^{(m)} \rangle = \int_{-\infty}^{\infty} r(t) x^{(m)*}(t-kT) e^{-j2\pi lFt} dt, \ m=1,2,\ldots,M.$  Thus,  $\widehat{\mathbf{H}}_R$  is a multi-window [18] Gabor filter consisting of Gabor analysis, multiplicative modification, and Gabor synthesis in each of the M branches.

If the partition  $\{\mathcal{R}_i\}$  is a wavelet-type tiling of the TF plane, a (conceptually analogous) multi-wavelet implementation of the robust Wiener filter can be developed.

**Variational Neighborhood Model.** Let  $\overline{W_s}^0(t, f)$  and  $\overline{W_n}^0(t, f)$  be nominal pseudo-WVS with mean energies  $\overline{E}_s^0 = \int_t \int_f \overline{W_s}^0(t, f) dt df$  and  $\overline{E}_n^0 = \int_t \int_f \overline{W_n}^0(t, f) dt df$ . Extending the stationary case [4, 5], we define variational neighborhood uncertainty classes for WVS as

$$\begin{split} \widetilde{\mathcal{S}} &= \left\{ \overline{W_s}(t,f) : \left\| \overline{W_s} - \overline{W_s}^0 \right\|_1 \le \epsilon \bar{E}_s^0 \right\} \\ \widetilde{\mathcal{N}} &= \left\{ \overline{W_n}(t,f) : \left\| \overline{W_n} - \overline{W_n}^0 \right\|_1 \le \epsilon \bar{E}_n^0 \right\} \end{split}$$

with fixed  $\epsilon > 0$ , combined with the requirement of fixed mean energies  $\int_t \int_f \overline{W_s}(t,f) dt df = \overline{E}_s^0$  and  $\int_t \int_f \overline{W_n}(t,f) dt df$  $= \overline{E}_n^0$ . The sets  $\widetilde{S}$  and  $\widetilde{N}$  can be shown to be convex.

<sup>&</sup>lt;sup>3</sup>The tilde will indicate TF approximations or TF versions.

<sup>&</sup>lt;sup>4</sup>Note that  $\widetilde{S}$ ,  $\widetilde{\mathcal{N}}$  are TF analogues of S,  $\mathcal{N}$ . Here and in what follows,  $\overline{W_s}(t, f)$  and  $\overline{W_n}(t, f)$  are "pseudo-WVS" that are not necessarily valid WVS but arbitrary TF functions that are (essentially) nonnegative. (We note that the WVS of an underspread process is essentially nonnegative [14, 15].)

In what follows, we define the nominal TF SNR  $\operatorname{SNR}^0(t, f) \triangleq \overline{W_s}^0(t, f) / \overline{W_n}^0(t, f)$  and use the abbreviation  $\overline{W}^0(t, f) \triangleq \overline{E_n}^0 \overline{W_s}^0(t, f) + \overline{E_s}^0 \overline{W_n}^0(t, f)$ . Extending [4], it can be shown that the least favorable pseudo-WVS are given by

$$\overline{W_s}^L(t,f) = \begin{cases} \frac{c_1}{E_s^0 + c_1 E_n^0} \overline{W}^0(t,f) & \text{for } (t,f) \in \mathcal{R}_1 \\ \overline{W_s}^0(t,f) & \text{for } (t,f) \in \mathcal{R}_0 \\ \frac{c_2}{E_s^0 + c_2 E_n^0} \overline{W}^0(t,f) & \text{for } (t,f) \in \mathcal{R}_2 , \end{cases}$$
$$\overline{W_n}^L(t,f) = \begin{cases} \frac{1}{E_s^0 + c_1 E_n^0} \overline{W}^0(t,f) & \text{for } (t,f) \in \mathcal{R}_1 \\ \overline{W_n}^0(t,f) & \text{for } (t,f) \in \mathcal{R}_0 \\ \frac{1}{E_s^0 + c_2 E_n^0} \overline{W}^0(t,f) & \text{for } (t,f) \in \mathcal{R}_2 . \end{cases}$$

Here  $\mathcal{R}_1$ ,  $\mathcal{R}_0$ , and  $\mathcal{R}_2$  are the TF regions where  $\mathrm{SNR}^0(t, f)$ is  $\langle c_1, \in [c_1, c_2]$ , and  $\rangle c_2$ , respectively, and the constants  $c_1, c_2$  are chosen such that  $\|\overline{W}_s^L - \overline{W}_s^0\|_1 = \epsilon \overline{E}_s^0$  and  $\|\overline{W}_n^L - \overline{W}_n^0\|_1 = \epsilon \overline{E}_n^0$  (which is always possible if  $\mathcal{S} \cap \mathcal{N} = \emptyset$ ). The corresponding TF SNR,  $\mathrm{SNR}^L(t, f) \triangleq \overline{W}_s^L(t, f) / \overline{W}_n^L(t, f)$ , equals  $c_1$ ,  $\mathrm{SNR}^0(t, f)$ , and  $c_2$  on  $\mathcal{R}_1$ ,  $\mathcal{R}_0$ , and  $\mathcal{R}_2$ , respectively, i.e.,  $\mathrm{SNR}^L(t, f)$  is  $\mathrm{SNR}^0(t, f)$  clipped from below and above. The Weyl symbol of the robust TF Wiener filter in (10) is then obtained as

$$L_{\tilde{\mathbf{H}}_{R}}(t,f) = \begin{cases} L_{\min} & \text{for } (t,f) \in \mathcal{R}_{1} \\ L_{\tilde{\mathbf{H}}_{W}^{0}}(t,f) & \text{for } (t,f) \in \mathcal{R}_{0} \\ L_{\max} & \text{for } (t,f) \in \mathcal{R}_{2} , \end{cases}$$
(12)

with  $L_{\widetilde{\mathbf{H}}_W^0}(t,f) = \overline{W_s}^0(t,f) / [\overline{W_s}^0(t,f) + \overline{W_n}^0(t,f)]$  and  $L_{\min} = \frac{c_1}{1+c_1}$ ,  $L_{\max} = \frac{c_2}{1+c_2}$ . Thus,  $L_{\widetilde{\mathbf{H}}_R}(t,f)$  is a clipped version of the Weyl symbol of the nominal TF Wiener filter,  $L_{\widetilde{\mathbf{H}}_W^0}(t,f)$ . Indeed, the potential performance loss of  $\widetilde{\mathbf{H}}_W^0$  is due to  $L_{\widetilde{\mathbf{H}}_W^0}(t,f)$  being too close to 0 (to 1) in TF regions where  $\mathrm{SNR}^0(t,f)$  is very small (large), resulting in a filter attenuation (gain) that is too store for *non*nominal WVS. Hence, a clipping of  $L_{\widetilde{\mathbf{H}}_W^0}(t,f)$  (which implies the clipping  $\mathrm{SNR}^0(t,f) \to \mathrm{SNR}^L(t,f)$  since  $L_{\widetilde{\mathbf{H}}_W^0}(t,f) = \mathrm{SNR}^0(t,f) / [\mathrm{SNR}^0(t,f) + 1]$ ) results in robustness.

 $\epsilon$ -Contamination Model. Again extending the stationary case [2], we define  $\epsilon$ -contamination uncertainty classes

$$\begin{split} \widetilde{\mathcal{S}} &= \left\{ \overline{W_s}(t,f): \ \overline{W_s}(t,f) = (1-\epsilon) \overline{W_s}^0(t,f) + \epsilon \, \overline{W_s}'(t,f) \right\} \\ \widetilde{\mathcal{N}} &= \left\{ \overline{W_n}(t,f): \ \overline{W_n}(t,f) = (1-\epsilon) \overline{W_n}^0(t,f) + \epsilon \, \overline{W_n}'(t,f) \right\}, \end{split}$$

with fixed  $\epsilon > 0$ , where  $\overline{W'_s}(t, f) \ge 0$ ,  $\overline{W'_n}(t, f) \ge 0$  are arbitrary up to the usual constraint of fixed mean energy, i.e.,  $\int_t \int_f \overline{W'_s}(t, f) dt df = \overline{E}^0_s$  and  $\int_t \int_f \overline{W'_n}(t, f) dt df = \overline{E}^0_n$ . The sets  $\widetilde{S}$  and  $\widetilde{\mathcal{N}}$  can be shown to be convex.

The least favorable pseudo-WVS are here obtained as

$$\overline{W}_{s}^{L}(t,f) = \begin{cases} c_{1}(1-\epsilon)\overline{W}_{n}^{0}(t,f) & \text{for } (t,f) \in \mathcal{R}_{1}, \\ (1-\epsilon)\overline{W}_{s}^{0}(t,f) & \text{for } (t,f) \in \mathcal{R}_{0} \cup \mathcal{R}_{2}, \end{cases}$$

$$\overline{W}_{n}^{L}(t,f) = \begin{cases} \frac{1}{c_{2}}(1-\epsilon)\overline{W}_{s}^{0}(t,f) & \text{for } (t,f) \in \mathcal{R}_{2}, \\ (1-\epsilon)\overline{W}_{n}^{0}(t,f) & \text{for } (t,f) \in \mathcal{R}_{0} \cup \mathcal{R}_{1}, \end{cases}$$

with  $c_1$ ,  $c_2$  chosen such that  $\overline{W}_s^L(t, f)$ ,  $\overline{W}_n^L(t, f)$  meet the mean energy constraints. The corresponding TF SNR is again a clipped version of  $\text{SNR}^0(t, f)$ , i.e.,  $\text{SNR}^L(t, f)$  equals  $c_1$ ,  $\text{SNR}^0(t, f)$ , and  $c_2$  on  $\mathcal{R}_1$ ,  $\mathcal{R}_0$ , and  $\mathcal{R}_2$ , respectively.



**Figure 1.** TF representations of signal and noise statistics as well as nominal and robust TF Wiener filters for  $\epsilon$ -contamination model ( $\epsilon = 0.1$ ): (a)  $\overline{W_s}^0(t, f)$ , (b)  $\overline{W_s}^L(t, f)$ , (c)  $\overline{W_n}^0(t, f)$ , (d)  $\overline{W_n}^L(t, f)$ , (e)  $L_{\widetilde{\mathbf{H}}_W}^0(t, f)$ , (f)  $L_{\widetilde{\mathbf{H}}_R}(t, f)$ .

Furthermore, the Weyl symbol of the robust TF Wiener filter in (10) equals the clipped version of  $L_{\widetilde{\mathbf{H}}_{W}^{0}}(t, f)$  given in (12). Note, however, that  $\mathcal{R}_{1}$ ,  $\mathcal{R}_{0}$ ,  $\mathcal{R}_{2}$  and  $L_{\min}$ ,  $L_{\max}$  are different due to the different uncertainty model.

## 4 SIMULATION RESULTS

Figs. 1(a) and 1(c) show nominal WVS of signal and noise. The least favorable WVS obtained for an  $\epsilon$ -contamination model with  $\epsilon = 0.1$  are depicted in Figs. 1(b) and 1(d). Fig. 1(f) shows that the Weyl symbol of the minimax robust TF Wiener filter  $\tilde{\mathbf{H}}_R$  is indeed a clipped version (with  $L_{\min} =$ 0.21,  $L_{\max} = 0.77$ ) of the Weyl symbol of the nominal TF Wiener filter  $\tilde{\mathbf{H}}_W^0$  depicted in Fig. 1(e).

Table 1 compares the MSEs achieved by  $\widetilde{\mathbf{H}}_W^0$  and  $\widetilde{\mathbf{H}}_R$  at nominal operating conditions  $(\overline{W}_s^0, \overline{W}_n^0)$  and at least favorable operating conditions  $(\overline{W}_s^L, \overline{W}_n^L)$  for several values of  $\epsilon$ . It is seen that the MSE variation is much smaller for  $\widetilde{\mathbf{H}}_R$ than for<sup>5</sup>  $\widetilde{\mathbf{H}}_W^0$ , i.e.,  $\widetilde{\mathbf{H}}_R$  is indeed robust with respect to a variation of operating conditions. We note that simulation results for the *p*-point model can be found in [8].

#### 5 CONCLUSION

We have introduced minimax robust time-varying Wiener filters that guarantee a certain performance within given

<sup>&</sup>lt;sup>5</sup>Here, it should be noted that while for  $\widetilde{\mathbf{H}}_R$  the worst-case operating conditions are given by  $(\overline{W}_s^L, \overline{W}_n^L)$ , the performance of  $\widetilde{\mathbf{H}}_W^0$  can be worse than at  $(\overline{W}_s^L, \overline{W}_n^L)$ .

| $\epsilon$  | 0.01  | 0.05  | 0.10  | 0.20  | 0.40  |
|---|-------|-------|-------|-------|-------|
| $	ilde{e}(L_{\widetilde{\mathbf{H}}_W^0};\overline{W_s}^0,\overline{W_n}^0)$            | 9.65  | 9.65  | 9.65  | 9.65  | 9.65  |
| $	ilde{e}(L_{\widetilde{\mathbf{H}}^0_W};\overline{W}^L_s,\overline{W}^L_n)$            | 10.35 | 12.60 | 15.66 | 20.99 | 30.64 |
| $	ilde{e}(L_{\widetilde{\mathbf{H}}_{R}};\overline{W_{s}}^{0},\overline{W_{n}}^{0})$    | 9.69  | 9.99  | 10.74 | 12.90 | 19.53 |
| $\tilde{e}(L_{\widetilde{\mathbf{H}}_{R}}; \overline{W}_{s}^{L}, \overline{W}_{n}^{L})$ | 10.33 | 12.26 | 14.48 | 17.40 | 19.55 |

**Table 1.** MSE obtained with  $\widetilde{\mathbf{H}}_W^0$  and  $\widetilde{\mathbf{H}}_R$  at nominal operating conditions  $(\overline{W}_s^0, \overline{W}_n^0)$  and at least favorable operating conditions  $(\overline{W}_s^L, \overline{W}_n^L)$  for several values of  $\epsilon$ .

uncertainty classes of nonstationary processes. A timefrequency reformulation of the minimax theory allowed us to replace the calculus of operators by the simpler calculus of functions. Intuitively appealing and simple closed-form expressions of robust time-frequency Wiener filters have been obtained for three important uncertainty models.

### **APPENDIX: PROOF OF THEOREM 2.1**

We show that (6) is necessary and sufficient for  $\mathbf{R}_s^L$ ,  $\mathbf{R}_n^L$  to satisfy the left-hand inequality in (7) with  $\mathbf{H}_L = \mathbf{H}_W^L$ ,

$$e(\mathbf{H}_W^L; \mathbf{R}_s, \mathbf{R}_n) \leq e(\mathbf{H}_W^L; \mathbf{R}_s^L, \mathbf{R}_n^L).$$
(13)

Our proof (see [19] for more details) is essentially an adaptation and combination of arguments in [4, 7].

To show that (6) is necessary for (13), we combine (13) with  $e_{\min}(\mathbf{R}_s, \mathbf{R}_n) \leq e(\mathbf{H}_W^L; \mathbf{R}_s, \mathbf{R}_n)$  and  $e(\mathbf{H}_W^L; \mathbf{R}_s^L, \mathbf{R}_n^L) = e_{\min}(\mathbf{R}_s^L, \mathbf{R}_n^L)$  to obtain  $e_{\min}(\mathbf{R}_s, \mathbf{R}_n) \leq e_{\min}(\mathbf{R}_s^L, \mathbf{R}_n^L)$  for all  $\mathbf{R}_s \in \mathcal{S}$ ,  $\mathbf{R}_n \in \mathcal{N}$ , which is (6).

We now prove that (6) is sufficient for (13). Let  $\mathbf{R}_s \in S$ and  $\mathbf{R}_n \in \mathcal{N}$ . One can show [19] that  $e_{\min}(\mathbf{R}_s, \mathbf{R}_n)$  is a concave function of  $\mathbf{R}_s$  and  $\mathbf{R}_n$ , so that

$$e_{\min}(\mathbf{R}_{s}^{\alpha}, \mathbf{R}_{n}^{\alpha}) \geq \alpha e_{\min}(\mathbf{R}_{s}, \mathbf{R}_{n}) + (1 - \alpha) e_{\min}(\mathbf{R}_{s}^{L}, \mathbf{R}_{n}^{L})$$
(14)

for  $0 \leq \alpha \leq 1$ , where  $\mathbf{R}_{s}^{\alpha} = \alpha \mathbf{R}_{s} + (1 - \alpha) \mathbf{R}_{s}^{L}$ ,  $\mathbf{R}_{n}^{\alpha} = \alpha \mathbf{R}_{n} + (1 - \alpha) \mathbf{R}_{n}^{L}$ . Due to the convexity of  $\mathcal{S}$  and  $\mathcal{N}$ , we have  $\mathbf{R}_{s}^{\alpha} \in \mathcal{S}$  and  $\mathbf{R}_{n}^{\alpha} \in \mathcal{N}$  for  $0 \leq \alpha \leq 1$ . Subtracting  $e_{\min}(\mathbf{R}_{s}^{L}, \mathbf{R}_{n}^{L})$  from both sides of (14) and dividing by  $\alpha$  yields

$$0 \geq \frac{1}{\alpha} f(\alpha) \geq e_{\min}(\mathbf{R}_s, \mathbf{R}_n) - e_{\min}(\mathbf{R}_s^L, \mathbf{R}_n^L)$$

where  $f(\alpha) \triangleq e_{\min}(\mathbf{R}_s^{\alpha}, \mathbf{R}_n^{\alpha}) - e_{\min}(\mathbf{R}_s^L, \mathbf{R}_n^L)$  and the upper bound follows from (6). Hence,  $\frac{1}{\alpha}f(\alpha)$  is bounded, so that its limit for  $\alpha \to 0^+$  exists and thus

$$0 \ge \lim_{\alpha \to 0^+} \frac{1}{\alpha} f(\alpha) .$$
 (15)

Let  $\mathbf{R}_r = \mathbf{R}_s + \mathbf{R}_n$ ,  $\mathbf{R}_r^{\alpha} = \mathbf{R}_s^{\alpha} + \mathbf{R}_n^{\alpha}$ , and  $\mathbf{R}_r^L = \mathbf{R}_s^L + \mathbf{R}_n^L$ . Using  $e_{\min}(\mathbf{R}_s, \mathbf{R}_n) = \operatorname{tr}\{\mathbf{R}_s\} - \operatorname{tr}\{\mathbf{R}_s(\mathbf{R}_r)^{-1}\mathbf{R}_s\}$ (cf. (3)) and  $\operatorname{tr}\{\mathbf{R}_s^{\alpha}\} = \operatorname{tr}\{\mathbf{R}_s^L\}$ , we obtain  $f(\alpha) = \operatorname{tr}\{\mathbf{R}_s^L(\mathbf{R}_r)^{-1}\mathbf{R}_s^L\} - \operatorname{tr}\{\mathbf{R}_s^{\alpha}(\mathbf{R}_r)^{-1}\mathbf{R}_s^{\alpha}\}$ . Separating terms and using RKHS techniques similar to [7] yields [19]

$$\lim_{\alpha \to 0^+} \frac{1}{\alpha} f(\alpha) = \operatorname{tr} \left\{ \mathbf{H}_W^L \mathbf{R}_r \mathbf{H}_W^{L+} \right\} - \operatorname{tr} \left\{ \mathbf{H}_W^L \mathbf{R}_r^L \mathbf{H}_W^{L+} \right\} + 2 \operatorname{tr} \left\{ \mathbf{H}_W^L \mathbf{R}_s^L \right\} - 2 \operatorname{Re} \left\{ \operatorname{tr} \left\{ \mathbf{H}_W^L \mathbf{R}_s \right\} \right\}$$

Adding tr{ $\mathbf{R}_s$ } and subtracting tr{ $\mathbf{R}_s^L$ } (which is allowed since tr{ $\mathbf{R}_s^L$ } = tr{ $\mathbf{R}_s$ }) and using  $e(\mathbf{H}; \mathbf{R}_s, \mathbf{R}_n) = tr{\mathbf{R}_s}$  $-2 \operatorname{Re}\{tr{\mathbf{H}_s}\} + tr{\mathbf{H}_r\mathbf{H}^+}$  (cf. (1)), we obtain

$$\lim_{\alpha \to 0^+} \frac{1}{\alpha} f(\alpha) = e(\mathbf{H}_W^L; \mathbf{R}_s, \mathbf{R}_n) - e(\mathbf{H}_W^L; \mathbf{R}_s^L, \mathbf{R}_n^L) \,.$$

With (15), this finally yields (13).

#### REFERENCES

- H. L. Van Trees, Detection, Estimation, and Modulation Theory, Part I. New York: Wiley, 1968.
- [2] S. A. Kassam and T. L. Lim, "Robust Wiener filters," J. Franklin Inst., vol. 304, pp. 171–185, Oct./Nov. 1977.
- [3] L. J. Cimini and S. A. Kassam, "Robust and quantized Wiener filters for p-point spectral classes," in Proc. Conf. Information Sciences and Systems, (Princeton, NJ), pp. 314-318, March 1980.
- [4] H. V. Poor, "On robust Wiener filtering," IEEE Trans. Autom. Contr., vol. 25, pp. 531–536, June 1980.
- [5] S. A. Kassam and H. V. Poor, "Robust techniques for signal processing: A survey," *Proc. IEEE*, vol. 73, pp. 433-481, March 1985.
- [6] S. Verdú and H. V. Poor, "On minimax robustness: A general approach and applications," *IEEE Trans. Inf. Theory*, vol. 30, pp. 328-340, March 1984.
- [7] R. J. Barton and H. V. Poor, "An RKHS approach to robust L<sub>2</sub> estimation and signal detection," *IEEE Trans. Inf. Theory*, vol. 36, pp. 485–501, May 1990.
- [8] G. Matz and F. Hlawatsch, "Robust time-varying Wiener filters: Theory and time-frequency formulation," in Proc. IEEE-SP Int. Sympos. Time-Frequency Time-Scale Analysis, (Pittsburgh, PA), Oct. 1998.
- [9] V. Barbu and T. Precupanu, Convexity and Optimization in Banach Spaces. Alphen aan de Rijn (The Netherlands): Sijthoff & Noordhoff, 1978.
- [10] W. Kozek, "Time-frequency signal processing based on the Wigner-Weyl framework," *Signal Processing*, vol. 29, pp. 77-92, Oct. 1992.
- [11] R. G. Shenoy and T. W. Parks, "The Weyl correspondence and time-frequency analysis," *IEEE Trans. Signal Process*ing, vol. 42, pp. 318–331, Feb. 1994.
- [12] G. Matz and F. Hlawatsch, "Time-frequency transfer function calculus (symbolic calculus) of linear time-varying systems (linear operators) based on a generalized underspread theory," J. Math. Phys., vol. 39, pp. 4041-4071, Aug. 1998.
- [13] P. Flandrin and W. Martin, "The Wigner-Ville spectrum of nonstationary random signals," in *The Wigner Distribution* — *Theory and Applications in Signal Processing* (W. Mecklenbräuker and F. Hlawatsch, eds.), pp. 211-267, Amsterdam (The Netherlands): Elsevier, 1997.
- [14] P. Flandrin, "On the positivity of the Wigner-Ville spectrum," Signal Processing, vol. 11, no. 2, pp. 187-189, 1986.
- [15] G. Matz and F. Hlawatsch, "Time-varying spectra for underspread and overspread nonstationary processes," in Proc. 32nd Asilomar Conf. Signals, Systems, Computers, (Pacific Grove, CA), Nov. 1998.
- [16] H. Kirchauer, F. Hlawatsch, and W. Kozek, "Timefrequency formulation and design of nonstationary Wiener filters," in *Proc. IEEE ICASSP-95*, (Detroit, MI), pp. 1549– 1552, May 1995.
- [17] F. Hlawatsch, Time-Frequency Analysis and Synthesis of Linear Signal Spaces: Time-Frequency Filters, Signal Detection and Estimation, and Range-Doppler Estimation. Boston: Kluwer, 1998.
- [18] Y. Y. Zeevi, M. Zibulski, and M. Porat, "Multi-window Gabor schemes in signal and image representations," in *Gabor Analysis and Algorithms: Theory and Applications* (H. G. Feichtinger and T. Strohmer, eds.), ch. 12, pp. 381–407, Boston (MA): Birkhäuser, 1998.
- [19] G. Matz and F. Hlawatsch, "Minimax robust time-frequency processing." Tech. Rep., Institute of Communications and Radio-Frequency Engineering, Vienna, Austria, 1998.