# ON SPATIO-FREQUENTIAL SMOOTHING FOR JOINT ANGLES AND TIMES OF ARRIVAL ESTIMATION OF MULTIPATHS

Ahmad Bazzi<sup>\*†</sup> Dirk T.M. Slock<sup>\*</sup> Lisa Meilhac<sup>†</sup>

\* EURECOM Mobile Comm's Dept., 450 route des Chappes, 06410 Biot - Sophia Antipolis, France Email: {bazzi,slock}@eurecom.fr

<sup>†</sup>CEVA-RivieraWaves, 400, avenue Roumanille Les Bureaux, Bt 6, 06410 Biot - Sophia Antipolis, France Email:{ahmad.bazzi, lisa.meilhac}@ceva-dsp.com

# ABSTRACT

A natural extension of the "Spatial" smoothing preprocessing technique is presented and analysed. It is well known that subspace methods do not work properly in the presence of coherent sources. In this paper, a "Spatio-Frequential" smoothing technique is described when the transmit OFDM symbol is received through multiple coherent signals using a uniform linear antenna array. After this preprocessing technique, one could efficiently apply any 2-dimensional subspace method to jointly estimate the angles and times of arrival of the incoming coherent signals. Simulation results demonstrate the potential of the proposed 2D smoothing method over existing separate spatial or frequential smoothing techniques.

*Index Terms*— Joint Estimation, Angle of Arrival, Time of Arrival, Spatio-Frequential, Smoothing

# 1. INTRODUCTION

The problem of Joint Angle and Delay of arrival Estimation, also known as JADE, is a well-known and challenging problem in the context of array signal processing. In a parametric approach [1], the system is very model-sensitive to perturbations, such as array calibration [2] and timing synchronisation [3]. Many algorithms have been developed to jointly estimate the angles and times of arrival of multiple paths, such as those based on Maximum Likelihood (ML), [4] and [5]. In [4], the authors manage to derive an iterative technique that transforms the ML problem into two sets of simple one-dimensional optimisation problems. In [5], the algorithm presented is a generalisation of the Iterative Quadratic ML (IQML) algorithm to the case of JADE. Under some conditions, algorithms based on ML are able to resolve coherent sources, which is the case of an indoor environment, where the received signal is a sum of scaled and delayed versions of the transmitted one.

Subspace algorithms are based on extraction of signal and noise subspaces. These algorithms are computationally much more efficient than ML techniques, but their performance is suboptimal compared to ML. The classical ones are MUSIC (derived independently in [6] and [7]), ROOT-MUSIC [8] which is a root finding version of MUSIC, and ESPRIT [9] that is based on shift-invariance properties of the data covariance matrix. Indeed, these algorithms were first designed for estimating the angles of arrival of multiple non-coherent sources. Extensions of the classical subspace methods were derived to jointly estimate angles and times of arrival of multiple signals, such as [10–17]. These methods will be referred to as 2D subspace techniques.

In the case of *coherent* sources, i.e. the received signal is a sum of scaled and delayed version of the transmitted signal, all subspace methods fail to estimate angles or times of arrival. Therefore, pre-processing techniques, such as Spatial smoothing, have been developed to cope with this issue [18] so as to estimate the angles of arrival using subspace techniques. The same preprocessing technique was applied in an attempt of estimating times of arrival using OFDM subcarriers in a single receive antenna case [19], thus the name frequency smoothing. Therefore, it only seems natural to propose a Spatio-Frequential smoothing technique to "decorrelate" the coherent signals so that one could efficiently estimate angles and times of arrival using 2D subspace techniques. The advantage of Spatio-Frequential smoothing is also discussed. The idea of 2D-Smoothing has been used in the context of 2D-arrays [20, 21] (i.e. rectangular arrays). However, this paper describes a new 2D preprocessing technique that is applicable to Single-Input-Multiple-Output (SIMO) systems that use multi-carrier transmit signals.

The paper is divided as follows: Section 2 presents the system model, assumptions, and problem formulation. A Recap of the JADE-MUSIC [10], or 2D-MUSIC, algorithm is given in Section 3. The *Spatio-Frequential* smoothing technique is described and analysed in Section 4, followed by simulations in Section 5. We conclude the paper in Section 6.

**Notations:** Upper-case and lower-case boldface letters denote matrices and vectors, respectively.  $(.)^T$  and  $(.)^{\dagger}$  represent the transpose and the transpose-conjugate operators.  $E\{.\}$  is the statistical expectation.  $\otimes$  represents the *Kronecker* product.  $\|\mathbf{X}\|_2$  is the *Frobenius* norm of matrix  $\mathbf{X}$ . The matrix  $\mathbf{I}_N$  is the identity matrix of dimensions  $N \times N$ . The symbol  $\blacksquare$  indicates the end of a proof.

### 2. SYSTEM MODEL

#### 2.1. Analytic Formulation

Consider an OFDM symbol s(t) composed of M subcarriers, impinging an array of N antennas via q multipath components, each arriving at AoAs  $\{\theta_1, \ldots, \theta_q\}$  and ToAs  $\{\tau_1, \ldots, \tau_q\}$ . In baseband, we could write the received signal of the  $l^{th}$  OFDM symbol at the  $n^{th}$  antenna as:

$$r_n(t,l) = \sum_{i=1}^{q} \gamma_i(l) a_n(\theta_i) s(t - \tau_i) + n_n(t,l)$$
(1)

This work was supported in part by RivieraWaves, a CEVA company, and a Cifre scholarship. EURECOM's research is partially supported by its industrial members, and by the EU projects ADEL (FP7) and HIGHTS (H2020).

with

$$s(t) = \begin{cases} \sum_{m=0}^{M-1} b_m e^{j2\pi m \bigtriangleup_f t} & \text{if } t \in [0,T] \\ 0 & \text{elsewhere} \end{cases}$$
(2)

where  $T = \frac{1}{\Delta_f}$  is the OFDM symbol duration,  $\Delta_f$  is the subcarrier spacing,  $b_m$  is the modulated information onto the  $m^{th}$  subcarrier.  $a_n(\theta)$  is the  $n^{th}$  antenna response to an incoming signal at angle  $\theta$ , the form of  $a_n(\theta)$  depends on the array geometry.  $\gamma_i(l)$  is the complex attenuation of the  $i^{th}$  multipath component. The term  $n_n(t,l)$ is background noise. Now, plugging (2) in (1) and sampling  $r_n(t,l)$ at regular intervals of  $k \triangleq k \frac{T}{M}$ , we get  $r_{n,k}(l) \triangleq r_n(k \frac{T}{M}, l)$  as:

$$r_{n,k}(l) = \sum_{i=1}^{q} \sum_{m=0}^{M-1} b_m \gamma_i(l) a_n(\theta_i) e^{j2\pi m (\frac{k}{M} - \Delta_f \tau_i)} + n_{n,k}(l)$$
(3)

Applying an *M*-point DFT to *M* samples collected from (3) (k = 0, ..., M - 1), we get:

$$R_{n,m}(l) = \sum_{k=0}^{M-1} r_{n,k}(l) e^{-j2\pi m \frac{k}{M}}$$

$$= b_m \sum_{i=1}^{q} \gamma_i(l) a_n(\theta_i) e^{-j2\pi m \Delta_f \tau_i} + N_{n,m}(l)$$
(4)

We assume prior knowledge of the symbols  $b_m$ . This is a valid assumption in Wi-Fi 802.11 systems since a fixed preamble is transmitted for channel estimation and other purposes. Thus, multiplying each  $R_{n,m}(l)$  by  $\frac{b_m^*}{|b_m|^2}$  and re-writing (4) in a compact form, we have

$$\mathbf{x}(l) = \mathbf{A}\boldsymbol{\gamma}(l) + \mathbf{n}(l), \qquad l = 1\dots L$$
(5)

where  $\mathbf{x}(l)$  and  $\mathbf{n}(l)$  are  $NM \times 1$  vectors given by

$$\mathbf{x}(l) = [R_{1,1}(l) \dots R_{1,M}(l) \dots R_{N,1}(l) \dots R_{N,M}(l)]^T \quad (6)$$

$$\mathbf{n}(l) = [N_{1,1}(l) \dots N_{1,M}(l) \dots N_{N,1}(l) \dots N_{N,M}(l)]^T$$
(7)  
and  $\boldsymbol{\gamma}(l)$  is the multipath vector of size  $q \times 1$ 

$$\boldsymbol{\gamma}(l) = \left[\gamma_1(l) \dots \gamma_q(l)\right]^T \tag{8}$$

The matrix **A** is an  $MN \times q$  matrix, i.e.

$$\mathbf{A} = [\mathbf{a}(\theta_1) \otimes \mathbf{c}(\tau_1) \dots \mathbf{a}(\theta_q) \otimes \mathbf{c}(\tau_q)]$$
(9)

with

and

$$\mathbf{a}(\theta) = [a_1(\theta) \dots a_N(\theta)]^T \tag{10}$$

$$\mathbf{c}(\tau) = [c_1(\tau) \dots c_M(\tau)]^T \tag{11}$$

In the rest of this paper, we consider a uniform linear antenna array spaced at half a wavelength, i.e.  $a_n(\theta) = e^{-j\pi(n-1)sin(\theta)}$ ; also, the subcarriers are uniformly spaced at each  $\Delta_f$ , i.e.  $c_m(\tau) = e^{-j2\pi\Delta_f(m-1)\tau}$ .

#### 2.2. Assumptions and Problem Statement

We assume the following:

- A1: A is full column rank.
- A2: The number of multipath components q is known.
- A3: The vector n(l) is additive Gaussian noise of zero mean and covariance σ<sup>2</sup>I<sub>MN</sub>, assumed to be white over space, frequencies, and symbols; we also assume that the noise is independent from the multipath coefficients.

Condition A1 is valid as long as:

- **A1.1**: q < MN.
- A1.2: We consider that ∀i ≠ j, (θ<sub>i</sub>, τ<sub>i</sub>) ≠ (θ<sub>j</sub>, τ<sub>j</sub>), that is all paths have distinct ToAs and AoAs, simultaneously, but it may happen that two, or more, paths arrive with the same ToAs, but different AoAs.
- A1.3: Let q<sup>θ</sup> be the number of distinct AoAs, i.e. θ<sup>1</sup>,..., θ<sup>q<sup>θ</sup></sup>; and let the following integers Q<sub>1</sub>,..., Q<sub>q<sup>θ</sup></sub> denote their corresponding multiplicity.

Note that  $\sum_{i=1}^{q^{\theta}} Q_i = q$ . This condition states that  $\max_i Q_i < N$ . That is the maximum number of paths arriving at the same time, i.e.  $\max_i Q_i$ , should be less than N.

A1.4: Similar to A1.3, let q<sup>τ</sup> be the number of distinct ToAs, i.e. τ<sup>1</sup>,..., τ<sup>q<sup>τ</sup></sup>; and let the following integers P<sub>1</sub>,..., P<sub>q<sup>τ</sup></sub> denote their corresponding multiplicity. This condition states that max<sub>i</sub> P<sub>i</sub> < M.</li>

Techniques for estimating the number of coherent sources could be done by the Minimum Description Length (MDL) criterion as described in [22], or by a Modified MDL (MMDL) criterion as recently presented in [23]. However, we assume knowledge of the number of sources, i.e. q is known. Any further assumptions will be mentioned. Now, we address our problem: Given  $\{\mathbf{x}(l)\}_{l=1}^{L}$  and q coherent sources, preprocess the data  $\{\mathbf{x}(l)\}_{l=1}^{L}$  so as to estimate the signal parameters  $\{(\theta_i, \tau_i)\}_{i=1}^{q}$  using a 2D subspace technique.

## 3. THE JADE-MUSIC ALGORITHM: A RECAP

The spatio-frequential covariance matrix is given by

$$\mathbf{R}_{xx} = E\{\mathbf{x}(l)\mathbf{x}^{\dagger}(l)\} = \mathbf{A}\mathbf{R}_{\gamma\gamma}\mathbf{A}^{\dagger} + \sigma^{2}\mathbf{I}_{MN}$$
(12)

where  $\mathbf{R}_{\gamma\gamma}$  is the covariance matrix of  $\gamma(l)$ . The matrix given in (12) is, usually, estimated through a sample average over snapshots, and is known as the sample covariance matrix, i.e.

$$\mathbf{R}_{xx} \simeq \frac{1}{L} \sum_{l=1}^{L} \mathbf{x}(l) \mathbf{x}^{\dagger}(l)$$
(13)

In what follows,  $\mathbf{R}_{xx}$  will be referred to as the sample covariance matrix, and not the true one. We denote  $\lambda_1 > \lambda_2 > \ldots > \lambda_{MN}$  the eigenvalues of  $\mathbf{R}_{xx}$ . Their corresponding eigenvectors are named  $\mathbf{u}_1, \mathbf{u}_2, \ldots, \mathbf{u}_{MN}$ . The sample covariance matrix in (13) is an input to most subspace algorithms for estimating the signal parameters, i.e. AoAs  $\{\theta_1 \ldots \theta_q\}$  and ToAs  $\{\tau_1 \ldots \tau_q\}$ . One of these algorithms is the JADE-MUSIC algorithm, which is a 2-D version of MUSIC. This algorithm is summarised as follows:

(1) Apply an eigenvalue decomposition of **R**<sub>xx</sub>.
 (2) Form the noise subspace matrix, i.e. **U**<sub>n</sub> = [**u**<sub>q+1</sub>...**u**<sub>MN</sub>].
 (3) Search for {θ̂<sub>i</sub>, τ̂<sub>i</sub>}<sup>q</sup><sub>i=1</sub> by

$$\{(\widehat{\theta}_i, \widehat{\tau}_i)\}_{i=1}^q = \underset{\theta, \tau}{\arg\max}\{\frac{1}{\|\mathbf{U}_n^{\dagger}[\mathbf{a}(\theta) \otimes \mathbf{c}(\tau)]\|_F^2}\} \quad (14)$$

The MUSIC algorithm is one of many subspace techniques, i.e. the extraction of a signal or noise subspace is required for further processing. Subspace techniques assume that the matrix  $\mathbf{R}_{\gamma\gamma}$  is full rank, otherwise the estimated subspaces do not reflect the true ones (See [18] for a mathematical argument). Furthermore, rank deficiency of  $\mathbf{R}_{\gamma\gamma}$  is due to coherence of multiple signals, or to insufficient number of snapshots, i.e. L < q. The spatial smoothing



Fig. 1: A spatio-frequential array of N = 3 antennas and M = 4 subcarriers partitioned into  $N_p = 2$  and  $M_p = 3$ , hence a total of  $K_M K_N = 4$  subcarrays.

pre-processing technique is known to "decorrelate" the sources, and therefore attain full rank of the matrix  $\mathbf{R}_{\gamma\gamma}$ .

In the following section, we present a 2D version of smoothing, i.e. *spatio-frequential* smoothing, and we show its advantage over conventional *spatial* or *frequential* smoothing techniques.

## 4. THE SPATIO-FREQUENTIAL PREPROCESSING TECHNIQUE

Recall that equation (5) gives the information on all subcarriers at all antennas. We shall use the notation (n, m) to index the  $m^{th}$  subcarrier and  $n^{th}$  antenna. Let the spatio-frequential array  $\{(i, j)\}_{i=1...N}^{j=1...M}$  of size MN be divided into overlapping subarrays of size  $M_pN_p$  ( $M_p$  and  $N_p$  being the number of subcarriers and antennas in the subarrays, respectively). Indeed, one could check that the total number of overlapping subarrays is equal to  $K_M K_N$ , where  $K_M = M - M_p + 1$  and  $K_N = N - N_p + 1$ .

To visualise how the subarrays are formed, we refer the reader to figure 1, where a setting of N = 3 antennas and M = 4 subcarriers is partitioned into overlapping subarrays of sizes  $N_p = 2$  and  $M_p = 3$ , and therefore a total of  $K_M K_N = 4$  subarrays.

Since the effective number of subcarriers and antennas used now are  $M_p$  and  $N_p$ , respectively, then (5) becomes

$$\mathbf{x}_{m,n}(l) = \bar{\mathbf{A}} \mathbf{D}_{\tau}^{m-1} \mathbf{D}_{\theta}^{n-1} \boldsymbol{\gamma}(l) + \mathbf{n}_{m,n}(l)$$
(15)

where  $\bar{\mathbf{A}} = [\mathbf{a}(\theta_1) \otimes \mathbf{c}(\tau_1) \dots \mathbf{a}(\theta_q) \otimes \mathbf{c}(\tau_q)]$  is an  $M_p N_p \times q$ matrix. The vectors  $\mathbf{a}(\theta)$  and  $\mathbf{c}(\tau)$  are the same as in (10) and (11) but with sizes  $N_p$  and  $M_p$  instead of N and M, respectively.  $\mathbf{D}_{\tau}^{m-1}$ and  $\mathbf{D}_{\theta}^{n-1}$  are the  $(m-1)^{th}$  and  $(n-1)^{th}$  power of the diagonal  $q \times q$  matrices  $\mathbf{D}_{\tau}$  and  $\mathbf{D}_{\theta}$ , given by

$$\mathbf{D}_{\tau} = \operatorname{diag} \left\{ c_2(\tau_1) \dots c_2(\tau_q) \right\}$$
(16a)

$$\mathbf{D}_{\theta} = \operatorname{diag} \left\{ a_2(\theta_1) \dots a_2(\theta_q) \right\}$$
(16b)

This means that  $\mathbf{x}_{m,n}(l)$  is an  $M_p N_p \times 1$  received vector on the subarray  $\{(i,j)\}_{j=n...N_p+n-1}^{i=m...M_p+m-1}$ . The covariance matrix of  $\mathbf{x}_{m,n}(l)$ 

in (15) after averaging over time snapshots is given as

$$\mathbf{R}_{m,n} = \bar{\mathbf{A}} \mathbf{D}_{\tau}^{m-1} \mathbf{D}_{\theta}^{n-1} \mathbf{R}_{\gamma\gamma} \mathbf{D}_{\theta}^{\dagger n-1} \mathbf{D}_{\tau}^{\dagger m-1} \bar{\mathbf{A}}^{\dagger} + \sigma^{2} \mathbf{I}_{M_{p}N_{p}}$$
(17)

The spatio-frequential smoothed covariance matrix is given by

$$\bar{\mathbf{R}} = \frac{1}{K_M K_N} \sum_{m=1}^{K_M} \sum_{n=1}^{K_N} \mathbf{R}_{m,n}$$
(18)

 $\mathbf{\bar{R}}$  could also be written as

$$\bar{\mathbf{R}} = \bar{\mathbf{A}}\bar{\mathbf{R}}_{\gamma\gamma}\bar{\mathbf{A}}^{\dagger} + \sigma^{2}\mathbf{I}_{M_{p}N_{p}}$$
(19)

where

$$\bar{\mathbf{R}}_{\gamma\gamma} = \frac{1}{K_M K_N} \sum_{m=1}^{K_M} \sum_{n=1}^{K_N} \mathbf{D}_{\tau}^{m-1} \mathbf{D}_{\theta}^{n-1} \mathbf{R}_{\gamma\gamma} \mathbf{D}_{\theta}^{\dagger n-1} \mathbf{D}_{\tau}^{\dagger m-1}$$
(20)

In a single carrier case, i.e.  $M = M_p = 1$ , it has been proven that the spatial smoothing technique ensures full rank of  $\mathbf{\bar{R}}_{\gamma\gamma}$  [18], given that  $q \leq K_N$ .

Analogously, in the single antenna but multi-carrier case, i.e.  $N = N_p = 1$ , the same technique has been applied in [19] and was referred to as frequency smoothing, in order to acheive full rank of  $\bar{\mathbf{R}}_{\gamma\gamma}$ , when  $q \leq K_M$ . However, in the general multi-antenna and multi-carrier case, we have the following:

<u>Theorem</u>: If the number of subarrays formed jointly over space and frequency is greater than the number of multipath components, i.e.  $q \leq K_M K_N$ , and the maximum number of paths arriving at the same time but with different angles is less than  $K_N$ , i.e.  $\max_i Q_i \leq K_N$ , and the maximum number of paths arriving at the same angles but with different times is less than  $K_M$ , i.e.  $\max_i P_i \leq K_M$ , then  $\bar{\mathbf{R}}_{\gamma\gamma}$  is of rank q.

*Proof*: Using (20),  $\bar{\mathbf{R}}_{\gamma\gamma}$  could be written as

$$\bar{\mathbf{R}}_{\gamma\gamma} = \mathbf{D}\mathbf{Q}\mathbf{D}^{\dagger} \tag{21}$$

where **D** is a  $q \times qK_M K_N$  matrix given by

$$\mathbf{D} = [\mathbf{T}, \mathbf{D}_{\theta}\mathbf{T}, \dots \mathbf{D}_{\theta}^{K_N - 1}\mathbf{T}]$$
(22a)

and

$$\mathbf{T} = [\mathbf{I}_q, \mathbf{D}_\tau, \dots, \mathbf{D}_\tau^{K_M - 1}]$$
(22b)

and **Q** is a block diagonal  $qK_MK_N \times qK_MK_N$  matrix expressed as

$$\mathbf{Q} = \frac{1}{K_M K_N} \mathbf{I}_{K_M K_N} \otimes \mathbf{R}_{\gamma\gamma}$$
(23)

Equation (21) can be expressed as follows

$$\bar{\mathbf{R}}_{\gamma\gamma} = \mathbf{W}\mathbf{W}^{\dagger} \tag{24}$$

with

and

$$\mathbf{W} = [\mathbf{T}_c, \mathbf{D}_{\theta} \mathbf{T}_c, \dots, \mathbf{D}_{\theta}^{K_N - 1} \mathbf{T}_c]$$
(25a)

 $\mathbf{T}_{c} = [\mathbf{C}, \mathbf{D}_{\tau}\mathbf{C}, \dots, \mathbf{D}_{\tau}^{K_{M}-1}\mathbf{C}]$ (25b)

where C is the square root of  $\frac{1}{K_M K_N} \mathbf{R}_{\gamma\gamma}$ :

$$\frac{1}{K_M K_N} \mathbf{R}_{\gamma\gamma} = \mathbf{C} \mathbf{C}^{\dagger} \tag{26}$$



**Fig. 2**: Spatial Smoothing with  $N_p = 2$ .





**Fig. 3**: Frequency Smoothing with  $M_p = 2$ .

**Fig. 4**: Spatio-Frequential Smoothing with  $N_p = 2$  and  $M_p = 3$ .

The rank of  $\mathbf{\bar{R}}_{\gamma\gamma}$  is equal to the rank of  $\mathbf{W}$ . Now, using the fact that the rank of a matrix is unchanged under column permutations, then we can write the following:

rank 
$$\mathbf{W} = \operatorname{rank} \begin{pmatrix} c_{11}\mathbf{v}_1 \otimes \mathbf{t}_1 & \cdots & c_{1q}\mathbf{v}_1 \otimes \mathbf{t}_1 \\ \vdots & \ddots & \vdots \\ c_{q1}\mathbf{v}_q \otimes \mathbf{t}_q & \cdots & c_{qq}\mathbf{v}_q \otimes \mathbf{t}_q \end{pmatrix}$$
 (27)

where  $c_{ij}$  is the  $(i, j)^{th}$  entry of **C**. Vectors  $\mathbf{v}_i$  and  $\mathbf{t}_i$   $(i = 1 \dots q)$  are of sizes  $1 \times K_N$  and  $1 \times K_M$ , respectively, given as

$$\mathbf{v}_i = [1, e^{-j\pi sin(\theta_i)}, \dots, e^{-j\pi (K_N - 1)sin(\theta_i)}]$$
(28a)

$$\mathbf{t}_i = [1, e^{-j2\pi\Delta_f \tau_i}, \dots, e^{-j2\pi\Delta_f (K_M - 1)\tau_i}]$$
(28b)

To prove that, for  $q \leq K_M K_N$ ,  $\max_i Q_i \leq K_N$ , and  $\max_i P_i \leq K_M$ , the matrix **W** is of rank q, we should prove the following: (a) **W** does not have an all-zero row, i.e. for a given row i, there exists at least one j such that  $c_{ij} \neq 0$ .

(**b**) The vectors  $\{\mathbf{v}_i \otimes \mathbf{t}_i\}_{i=1}^q$  are linearly independent.

The proof of (a) is found in [18]. As for (b), let **H** be a  $K_M K_N \times q$  matrix of columns  $\{\mathbf{v}_i \otimes \mathbf{t}_i\}_{i=1}^q$ . The matrix **H** is full column rank under the following three conditions:

**(b.1)**  $q \leq K_M K_N$ . (Similar to A1.1)

(b.2)  $\max_i Q_i \leq K_N$ . (Similar to A1.3)

**(b.3)**  $\max_i \dot{P}_i \leq K_M$ . (Similar to A1.4)

Conditions (b.1) till (b.3) are sufficient to attain full rank of  $\bar{\mathbf{R}}_{\gamma\gamma}$ . But, in order for subspace methods to work properly, one should also have that  $\bar{\mathbf{A}}$  (see (15)) is full column rank. Note that  $\bar{\mathbf{A}}$  has dimensions  $N_p M_p \times q$ . This is valid when  $q \leq M_p N_p$  (Similar to **A1.1**),  $\max_i Q_i \leq N_p$  (Similar to **A1.3**), and  $\max_i P_i \leq M_p$  (Similar to **A1.4**). In general, one must have:

(c.1)  $q \leq \min\{K_M K_N, M_p N_p\}.$ 

(c.2)  $\max_i Q_i \leq \min\{K_N, N_p\}.$ 

$$(\mathbf{c.3}) \max_i P_i \le \min\{K_M, M_p\}$$

Finally, the advantage of *spatio-frequential* smoothing is that it offers  $K_M K_N$  subarrays to smooth over, in contrast to *spatial* and *frequential* smoothing that naturally provide  $K_N$  and  $K_M$  subarrays, respectively. Therefore, one could be able to resolve more coherent sources, as given in (**b.1**). This advantage is, also, presented through simulations.

# 5. SIMULATIONS

Simulation results are presented to show the advantage of *spatio-frequential* smoothing over the conventional *spatial* and *frequential* 

smoothing. Simulations have been done with N = 3 antennas and M = 4 subcarriers at SNR = 20dB. The subcarrier spacing is chosen  $\triangle_f = 3.125$  MHz. We have fixed q = 4 paths, where their corresponding angles and times of arrival are  $(\theta_1, \tau_1) = (0^\circ, 40 \text{ nsec})$ ,  $(\theta_2, \tau_2) = (60^\circ, 100 \text{ nsec})$ ,  $(\theta_3, \tau_3) = (-20^\circ, 150 \text{ nsec})$  and  $(\theta_4, \tau_4) = (50^\circ, 200 \text{ nsec})$ . The complex attenuation vector  $\gamma$  is fixed to a constant arbitrary value. Finally, L = 3 snapshots were collected.

Figure 2 shows the JADE spectrum after preprocessing only by spatial smoothing, i.e.  $M = M_p = 4$  and  $N_p = 2$ . Indeed, there is an ambiguity in detecting the 4 peaks corresponding to the true angles and times of arrival due to insufficient number of subarrays to smooth over, i.e. only  $K_N = 2 < q$  spatial subarrays are available. The same argument is done when one applies only frequency smoothing, i.e.  $N = N_p = 3$  and  $M_p = 2$ . In that case, one will have  $K_M = 3 < q$  subarrays to smooth over. As a result, false peaks appear in figure 3.

To this end, we could see that we need at least q = 4 subarrays to smooth over. This is done by preprocessing through spatiofrequential smoothing. Choosing  $N_p = 2$  and  $M_p = 3$  would lead to  $K_N K_M = 4$  subarrays in total. After smoothing over space and frequencies, one could observe 4 clear peaks corresponding to the true angles and times of arrival of the 4 paths in figure 4.

# 6. CONCLUSION

We have presented a 2D smoothing preprocessing technique, applied to a *Spatial-Frequential* array, to "decorrelate" multipath components. Then, any 2D subspace algorithm could be applied to estimate the times and angles of arrivals of the different paths. The 2D smoothing technique presented here, naturally, offers more subarrays to smooth over and, therefore, one could be able to resolve more coherent paths.

#### REFERENCES

- H. Krim and M. Viberg, "Two decades of array signal processing research: the parametric approach," IEEE Signal Processing Magazine, vol. 13, no. 4, pp. 6794, Jul 1996.
- [2] Lin M. and Yang L., "Blind Calibration and DOA Estimation With Uniform Circular Arrays in the Presence of Mutual Coupling," Antennas and Wireless Propagation Letters, vol. 5, pp. 315318, December 2006.

- [3] A. Bazzi, D. T.M. Slock, and L. Meilhac, "On the effect of random snapshot timing jitter on the covariance matrix for JADE estimation," EUSIPCO 2015, 23rd European Signal Processing Conference, Nice, France, August 31st-September 4th, 2015.
- M. Wax and A. Leshem, "Joint estimation of time delays and directions of arrival of multiple reflections of a known signal," IEEE Trans. Signal Processing, vol. 45, pp. 24772484, Oct. 1997
- [5] A. Bazzi, D. T.M. Slock, and L. Meilhac, "Efficient maximum likelihood joint estimation of angles and times of arrival of multiple paths," in Proc. of IEEE GLOBECOM Workshop on Localization for Indoors, Outdoors, and Emerging Networks, 2015.
- [6] R. 0. Schmidt, "Multiple emitter location and signal parameter estimation," IEEE Trans. Antennas and Propagation, vol. AP-34, pp. 276- 280, 1986.
- [7] G. Bienvenu and L. Kopp, "Adaptivity to background noise spatial coherence for high resolution passive methods," in Proc. ICASSP80, 1980, pp. 307-310.
- [8] A. J. Barabell, "Improving the resolution performance of eigenstructure-based direction finding algorithms," in Proc. IEEE ICASSP, 1983, pp. 336-339.
- [9] R. Roy and T. Kailath, "ESPRIT-Estimation of signal parameters via rotational invariance techniques," IEEE Trans. Acoust., Speech, Signal Processing, vol.37, no. 7, pp. 984-995, July 1989.
- [10] M. C. Vanderveen, C. Papadias, and A. Paulraj, "Joint angle and delay estimation (JADE) for multipath signals arriving at an antenna array," IEEE Commun. Lett., vol. 1, no. 1, pp. 1214, 1997
- [11] A.J. Van Der Veen, M. C. Vanderveen, and A. J. Paulraj, "Joint angle and delay estimation using shift-invariance properties," IEEE Signal Processing Letters 1997.
- [12] Y.Y.Wang, J.T.Chen, and W.H.Fang, "TST-music for joint DoA-delay estimation," IEEE Trans. on Signal Processing, 2001.
- [13] Y.-F. Chen and M.D. Zoltowski, "Joint angle and delay estimation for DS-CDMA with application to reduced dimension space-time RAKE receivers," IEEE Trans. Acoust., Speech, Signal Processing,2933 - 2936, vol.5, March 1999.
- [14] S. Al-Jazzar and J. Caffery, "ESPRIT-based joint AOA/delay estimation for CDMA systems," Wireless Communications and Networking Conference, 2244 - 2249 Vol.4, 2004.
- [15] A. N. Lemma, A.-J. van der Veen, and E. F. Deprettere, Analysis of joint angle-frequency estimation using ESPRIT, IEEE Trans. Signal Process., vol. 51, pp. 12641283, May 2003.
- [16] J.D. Lin, W.H. Fang, Y.Y. Wang, and J.T. Chen, "FSF MUSIC, for joint DOA and frequency estimation and its performance analysis," IEEE Trans. Signal Process., vol. 54, no. 12, pp. 45294542, Dec. 2006.
- [17] Zhang, X., G. Feng, and D. Xu, "Blind direction of angle and time delay estimation algorithm for uniform linear array employing multi-invariance MUSIC," Progress In Electromagnetics Research Letters, Vol. 13, 1120, 2010
- [18] T. J. Shan, M. Wax, and T. Kailath, "On spatial smoothing for direction of arrival estimation of coherent signals," IEEE Trans. ASSP, vol. 33, no.4, pp. 806-811, Apr. 1985.

- [19] M. Oziewicz, "On application of MUSIC algorithm to time delay estimation in OFDM channels," IEEE Trans. Broadcasting, vol. 51, no.2, pp. 249255, June 2005.
- [20] P. Pal and P. P. Vaidyanathan, "Nested arrays in two dimensions, Part I: Geometrical considerations," IEEE Trans. on Signal Processing, vol. 60, No. 9, pp. 4694–4705, Sept. 2012.
- [21] P. Pal and P. P. Vaidyanathan, "Nested arrays in two dimensions, Part II: Application in two dimensional array processing," IEEE Trans. on Signal Processing, vol. 60, No. 9, pp. 4706–4718, Sept. 2012.
- [22] M. Wax and I. Ziskind, "Detection of the number of coherent signals by the MDL principle," Acoustics, Speech and Signal Processing, IEEE Transactions on, vol. 37, no. 8, pp. 11901196, aug 1989.
- [23] A. Bazzi, D. T.M. Slock, and L. Meilhac, "Detection of the number of superimposed signals using modified MDL criterion: A random matrix approach," IEEE International Conference on Acoustics, Speech, and Signal Processing (ICASSP), 2016.